

| <b>Model</b>                   |   |
|--------------------------------|---|
| Model Name                     | Chroma 410  |
| Model Number                   | CSAZ-410A   |
| <b>Specifications</b>          |   |
| Type                           | ATX Mid Tower   |
| Color                          | Black(exterior)/Black(interior)   |
| Side Panel Window              | Tempered Glass with rubber mounts   |
| Max CPU Cooler Height          | Up to 162mm   |
| Max Video Card Length          | Up to 400mm Long Video Card   |
| Power Supply                   | Not included  |
| Motherboard Compatibility      | ATX, Micro ATX  |
| <b>Expansion</b>               |   |
| External 5.25" Drive Bays      | 0   |
| Internal 2.5" Drive Bays       | Up to 6   |
| Internal 3.5" Drive Bays       | Up to 2   |
| Expansion Slots                | 7(Horizontal)+2(Vertical)   |
| Top Ports                      | 2xUSB3.0, 2xUSB2.0, HD Audio  |
| <b>Physical Specifications</b> |   |
| Dimensions (HxWxD)             | 520x205x500mm / 20.5x8.1x19.7 inches  |
| Weight                         | 6.82 kg / 15.0 lbs  |
| <b>Features</b>                |   |
| Digital RGB Light Effects      | Digital RGB light on the front. All digital RGB light devices controlled by RF Remote (included) or motherboard.  |
| Tempered Glass Side Window     | High-quality tempered glass side windows allow for clear visuals to inner components  |
| Available Fan Ports            | 2x120mm Fan ports on the top<br>3x120mm or 2x140mm Fan ports in the front<br>(2x120mm Black Fans included)<br>1x120mm Fan port in the rear<br>(1x120mm PRISMA-Digital RGB Fan included) |
| Dust Filters                   | Dustproof PVC Net x2 on bottom of Chassis   |
| Water Cooling                  | Supports radiators up to 240mm on top / 360mm in front  |
| Isolated Chamber               | Power supply is housed inside its own isolated chamber, preventing its heat from affecting other components   |
| Easy Installation Cooler       | A pre-cut hole for easy installation of CPU Cooler, eliminating the need to remove the motherboard  |